

## XT-6317/XT-6517 JUMPER SETTING

- **JLVDS\_SEL1: LVDS Voltage Selection**
  - Pin 1-2 Short : 3.3V
  - Pin 2-3 Short : 5V
- **JP1: LED Panel Resolution Selection**
  - Pin 1-2 、 7-8 Short & Pin 3-4 、 5-6 Open : (1280\*10240 Dual 24Bits)
- **JP2: LCD POWER Selection**
  - Pin 1-2Short : NORMAL USB TOUCH
  - Pin 1-2Short : Resistive touch sound used
- **JCOM\_SEL1: COM1/COM2 PORT DC SUPPLY SELECT**
  - Pin 1-3 Short : COM1 Pin1 connected as 12V DC
  - Pin 3-5 Short : COM1 Pin1 connected as DCD
  - Pin 2-4 Short : COM2 Pin1 connected as 12V DC
  - Pin 4-6 Short : COM2 Pin1 connected as DCD
- **JCOM\_SEL2 : COM3/COM4 PORT DC SUPPLY SELECT**
  - Pin 1-3 Short : COM3 Pin1 connected as 12V DC
  - Pin 3-5 Short : COM3 Pin1 connected as DCD
  - Pin 2-4 Short : COM4 Pin1 connected as 12V DC
  - Pin 4-6 Short : COM4 Pin1 connected as DCD
- **JCR\_SEL1: For CR open/close status port selection**
  - Pin 1-3 、 2-4 Short: For COM1
  - Pin 3-5 、 4-6 Short : For COM5
- **COM1~COM6 : +5V through BIOS ; VGA +12V through BIOS**
  - Press ESC to access Advanced/Miscellaneous Configuration
  - VGA DSUB 12V : Disabled
  - COM1 DB9 5V : Disabled
  - COM2 DB9 5V : Disabled
  - COM3 DB9 5V : Disabled
  - COM4 DB9 5V : Disabled
  - COM5 DB9 5V : Disabled
  - COM6 DB9 5V : Disabled

※ DIP SWITCH1 (SW1) :

SWITCH 1		FUNCTION
1 On	2 OFF	Default
1 OFF	2 ON	Clear CMOS
3	ON	Disable Flash Descriptor Security (Can override ME code)
	OFF	Enable security measures in the Flash Descriptor (Default)

