

FT-6615 JUMPER SETTING

- **JP1 : CF Card LED**
Short : CF Card LED
Open: W/O CF Card LED or Raid HDD2
- **JP2 : HDD1 LED**
Short : HDD LED
Open: W/O HDD1-LED or W/ Raid HDD1
- **JP3 : Power indicator LED for green color**
Open: W/O LED
Short: With Green Light Standby
- **JP4 : Reserved**
- **JP5 、 JP6 : Touch Control Setting**
USB Touch : JP5 、 JP6 All Open
PS2 Touch : JP5 、 JP6 Pin3-5 and Pin4-6 Short
RS232 Touch : JP5 、 JP6 Pin1-3 and Pin2-4 Short
- **CN6 : Mouse/Clock/Data**
Pin 1-2,3-4 Short : Internal PS2 Mouse
All Open: Reserve for PS2 Touch
- **JP7 : CMOS DATA CONTROL**
Pin 1-2 Short: Normal
Pin 2-3 Short : clear CMOS
- **JP8 : LAN setting**
Open: Disable LAN
Short : Enable LAN
- **JP9 : COM1/COM2 Pin9 connected Setting**
Pin 1-3 Short : COM1 Pin9 connected to 5 V DC
Pin 3-5 Short : COM1 Pin9 connected as RI
Pin 2-4 Short : COM2 Pin9 connected to 5 V DC
Pin 4-6 Short : COM2 Pin9 connected as RI
- **JP10 :COM1/COM2 Pin1 connected Setting**
Pin 1-3 Short : COM1 Pin1 connected to 12V
Pin 3-5 Short : COM1 Pin1 connected to DCD
Pin 2-4 Short : COM2 Pin1 connected to 12V
Pin 4-6 Short : COM2 Pin1 connected to DCD
- **JP11 :COM3/COM4 Pin1 connected Setting**
Pin 1-3 Short : COM3 Pin1 connected to 12V
Pin 3-5 Short : COM3 Pin1 connected to DCD
Pin 2-4 Short : COM4 Pin1 connected to 12V
Pin 4-6 Short : COM4 Pin1 connected to DCD

- **JP12 : COM3/COM4 Pin9 connected Setting**
 Pin 1-3 Short : COM3 Pin9 connected to 5 V DC
 Pin 3-5 Short : COM3 Pin9 connected as RI
 Pin 2-4 Short : COM4 Pin9 connected to 5 V DC
 Pin 4-6 Short : COM4 Pin9 connected as RI
- **JP13 : UPS Detected**
 Pin 1-2 Short: DCD
 Pin 2-3 Short: UPS Detected
- **JP14 : 12V DC SUPPLY SELECT FOR CRT**
 Open: no 12V Supply to CRT port
 Short: 12V Output supply to CRT port

