

## PP-6906W Jumper Setting

- DIP SWITCH 1:

On bottom cover of the PP-6906W series thermal printer, there is screwed a metal plate for setup window.

SWITCH 1	FUNCTION
<b>1</b>	<b>Download MCU</b>
<b>OFF</b>	<b>ARM</b>
ON	RX
<b>2</b>	<b>Interface</b>
OFF	LAN
<b>ON</b>	<b>WiFi</b>
<b>3</b>	<b>Cut Paper after Cover Return</b>
<b>OFF</b>	<b>Enable</b>
ON	Disable
<b>4</b>	<b>Full Cut Paper</b>
<b>OFF</b>	<b>Disable</b>
ON	Enable
<b>5</b>	<b>Busy condition</b>
<b>OFF</b>	<b>Enable</b>
ON	Disable
<b>6</b>	<b>Before Cut Paper</b>
<b>OFF</b>	<b>Normal Cut</b>
ON	Cut and without paper feed
<b>7</b>	<b>Auto cutter</b>
<b>OFF</b>	<b>Enable</b>
ON	Disable
<b>8</b>	<b>Firmware update Mode</b>
<b>OFF</b>	<b>Disable (Fixed to OFF)</b>
ON	Enable

## ● SOFTWARE SWITCH 2:

SWITCH 2	FUNCTION
<b>1</b>	<b>Software Switch Selection</b>
<b>OFF</b>	<b>Set Hardware Switch 1 Valid</b>
ON	Set Hardware Switch 1 Invalid (Software switch 1 will valid instead of hardware switch 1)
<b>2</b>	<b>Paper width</b>
<b>OFF</b>	<b>80mm</b>
ON	58mm
<b>3</b>	<b>Printable width</b>
<b>OFF</b>	<b>512dots</b>
ON	576dots
<b>4</b>	<b>Paper Feed Back</b>
<b>OFF</b>	<b>Enable</b>
ON	Disable
<b>5</b>	<b>Raster Bitmap Printing</b>
<b>OFF</b>	<b>Batch Print</b>
ON	Line Print
<b>6</b>	<b>Parity Check</b>
<b>OFF</b>	<b>NONE</b>
ON	EVEN
<b>7</b>	<b>Handshaking</b>
<b>OFF</b>	<b>DTR/DSR</b>
ON	XON/XOFF
<b>8</b>	<b>&lt; CR &gt; Auto Line Feed</b>
<b>OFF</b>	<b>Disable</b>
ON	Enable

● SOFTWARE SWITCH 3:

SWITCH 3			FUNCTION
<b>1</b>			<b>UPOS Write</b>
<b>OFF</b>			<b>Disable</b>
ON			Enable
<b>2</b>			<b>Beep Sound after Cut paper</b>
<b>OFF</b>			<b>Disable</b>
ON			Enable
<b>3</b>	<b>4</b>	<b>5</b>	<b>Print Density</b>
<b>OFF</b>	<b>OFF</b>	<b>OFF</b>	<b>100%</b>
ON	OFF	OFF	110%
OFF	ON	OFF	120%
ON	ON	OFF	130%
<b>6</b>			<b>Print Speed</b>
<b>OFF</b>			<b>170mm/s</b>
ON			200mm/s
<b>7</b>			<b>Thai Font mode</b>
<b>OFF</b>			<b>1 PASS</b>
ON			3 PASS
<b>8</b>			<b>Cover Open Message</b>
<b>OFF</b>			<b>Disable</b>
ON			Enable

● SOFTWARE SWITCH 4:

SWITCH 4		FUNCTION
<b>1</b>		<b>Print Speed 120mm/s</b>
<b>OFF</b>		<b>Disable</b>
ON		Enable
<b>2</b>	<b>3</b>	<b>Barcode Height Reduction</b>
<b>OFF</b>	<b>OFF</b>	<b>Disable</b>
ON	OFF	Reduce 25%
OFF	ON	Reduce 50%
ON	ON	Reduce 75%
<b>4</b>	<b>5</b>	<b>Line Space Reduction</b>
<b>OFF</b>	<b>OFF</b>	<b>Disable</b>
ON	OFF	Reduce 25%
OFF	ON	Reduce 50%
ON	ON	Reduce 75%
<b>6</b>	<b>7</b>	<b>Line Feed Reduction</b>
<b>OFF</b>	<b>OFF</b>	<b>Disable</b>
ON	OFF	Reduce 25%
OFF	ON	Reduce 50%
ON	ON	Reduce 75%
<b>8</b>		<b>Reserve</b>
<b>OFF</b>		Reserve
ON		Reserve

※ JP1: Use for Mac address download.

JP1	FUNCTION
Open	Normal Mode
Short	Mac download mode