

KS-6715 JUMPER SETTING

- **J3 : CPU CLOCK SELECT**

| 5-6 | 3-4 | 1-2 | | |
|-----------|-----------|------------|------------|-----------|
| FSLA | FSLC | FSLB | CPU | PCI |
| ON | ON | ON | 266.66 | 33 |
| OFF | ON | ON | 133.33 | 33 |
| ON | ON | OFF | 200 | 33 |
| OFF | ON | OFF | 166.66 | 33 |
| OFF | OFF | ON | 100 | 33 |
| OFF | OFF | OFF | Reserved | |

- **JP1 : LCD PANEL POWER SELECT**

Pin 1-2 Short : 3.3V for 15" LCD Panel

Pin 2-3 Short : 5V for 17" LCD Panel

- **JP2 : MICRO PROCESSOR FIRMWARE UPDATE HEADER**

- **JP3: EUP/WAKE ON OPTION**

OPEN: To support EUP But no support LAN/Alarm/modem wake up & power fail after power on function

Short : Disable EUP support but support LAN/Alarm/modem wake up & power fail after power on function

- **JP4: COM1/COM2 DC SUPPLY SELECT**

Pin 1-3 Short : COM1 support 5V function

Pin 3-5 Short : COM1 Pin9 connected as RI

Pin 2-4 Short : COM2 support 5V function

Pin 4-6 Short : COM2 Pin9 connected as RI

- **JP5: COM1/COM2 DC SUPPLY SELECT**

Pin 1-3 Short : COM1 Pin1 connected to 12V

Pin 3-5 Short : COM1 Pin1 connected as DCD

Pin 2-4 Short : COM2 Pin1 connected to 12V

Pin 4-6 Short : COM2 Pin1 connected as DCD

- **JP6: COM3/COM4 DC SUPPLY SELECT**

Pin 1-3 Short : COM3 support 5V function

Pin 3-5 Short : COM3 Pin9 connected as RI

Pin 2-4 Short : COM4 support 5V function

Pin 4-6 Short : COM4 Pin9 connected as RI

- **JP7: COM3/COM4 DC SUPPLY SELECT**

Pin 1-3 Short : COM3 Pin1 connected to 12V

Pin 3-5 Short : COM3 Pin1 connected as DCD

Pin 2-4 Short : COM4 Pin1 connected to 12 V

Pin 4-6 Short : COM4 Pin1 connected as DCD

- **JP8 、 JP9 : TOUCH TYPE SELECT**

All Open : On Board Touch Disable (For MTC Touch)

Short :On Board USB Panel Touch Enable

- **DIP SWITCH1**

| SWITCH 1 | | FUNCTION |
|----------|-------|------------------------------------|
| 1 ON | 2 OFF | Normal |
| 1 OFF | 2 ON | Clear CMOS |
| 3 | ON | Windows OS (Win98, Win2k, WinXP) |
| | OFF | Linux or WinCE |
| 4 | ON | ELO Touch Panel or OEM Touch Panel |
| | OFF | Fujitsu Touch Panel |
| 5 | ON | MS-DOS |
| | OFF | Windows, Linux, WinCE |
| 6 | ON | Reserved |
| | OFF | Reserved |
| 7 | ON | Reserved |
| | OFF | Reserved |
| 8 | ON | COM4 Disable |
| | OFF | COM4 Enable |

